



CASAMBI  
READY



**Technische Daten *Technical data***

Artikelnummer <i>Part no.</i>	808948
Typ <i>Type</i>	DE4DABT14-422
Versorgungseingang <i>Power supply input</i>	10..24 Vdc
Funksignal <i>Radio signal</i>	2,4..2,483 GHz; 4 dBm
Alternative Ansteuerung <i>Alternative control</i>	Taster, DALI <i>push button, DALI</i>
Max. Ausgangsleistung <i>Max. output power</i>	4,4 A
PWM Frequenz <i>PWM frequency</i>	130,2 Hz / 488 Hz
Umgebungstemperatur <i>Ambient temperature (ta)</i>	-20..+40 °C
Max. Bemessungstemperatur <i>Rated Max. temp. (tc)</i>	85 °C
IP Schutzklasse <i>IP protection level</i>	20
Abmessungen <i>Dimensions</i>	56,6 x 35,8 x 22,6 mm

- LED-Dimmer zum komfortablen Bedienen mit Tablet oder Smartphone (Apple, Android) mit der CASAMBI-App
- Für 1..4 Kanäle, CCT und RGB+W
- Kostenlose App von CASAMBI (Apple/Android):
  - Regeln der Helligkeit und Lichtfarbe
  - Konfigurieren von Leuchten und Leuchten-Netzwerken
  - Erstellen von Szenen und Animationen (Farbverläufe)
  - Neue Geräte werden automatisch erkannt
  - Intelligente Timer- und Galeriefunktionen
  - Freigabeoptionen festlegen („nur ich“, „alle“, „nur mit Passwort“,....)
- Gateway wird nicht benötigt, Einrichtung aber möglich
- Integrierte Antenne
- Steckkontakte für optimale Vormontage

- *LED-Dimmer, easily operated by smartphone or tablet (Apple, Android) with the CASAMBI app*
- *For 1..4 channels, CCT and RGB+W*
- *Free App from CASAMBI (Apple/Android):*
  - *lighting control (colour/dim level)*
  - *configuration of luminaires and luminaires networks*
  - *creation of scenes and animations (colour gradient)*
  - *automatic detection of new devices*
  - *intelligent timer and gallery function*
  - *protection settings of your luminaires network („just me“, „with password“,....)*
- *You can setup a gateway, but it is not necessary*
- *Integrated antenna*
- *Plug-in terminals for optimized pre-assembling*



Bitte beachten Sie die „Allgemeinen Hinweise“.

