

TRAFO VARIALUCE TOUCH HALO-LED TBT 12Vac - MAX 60W TRAFO DIMMER TOUCH HALO-LED TBT 12Vac - MAX 60W



Lampada alogena tradizionale
Traditional halogen lamp
12Vac - 20÷60W



R111



G4



MR16


Lampada LED dimmerabile
Dimmable LED lamp
12Vac - 3÷60W
* Max 4 / 5 Lamps



| Codice Code | LPH ↓mm | Vac IN | Carico Load | W | Hz | ta °C | Vout Vac | PCS | CCM cm³ |
|----------------|------------|-----------|----------------|---------------|-------|----------|-------------|-----|---------|
| RL7323HLEDS | 106x57x34 | 220-240 | HALO LED * | 20÷60 3÷60 | 50/60 | -15...35 | 12 | 25 | 6.800 |
| RL7323HALEDST | 106x57x34 | 220-240 | HALO LED * | 20÷60 3÷60 | 50/60 | -15...35 | 12 | 25 | 6.800 |
| RL7327HALEDPS | 106x57x34 | 220-240 | HALO LED * | 20÷60 3÷60 | 50/60 | -15...35 | 12 | 25 | 6.800 |



Dimensioni (mm) - Dimensions (mm)



Caratteristiche tecniche

Trasformatore elettronico indipendente dimmerabile, per lampade alogene E LED

- Regolazione sensoriale o a pulsante continua
- Sensore indipendente dalla polarità di rete
- Distanza tra scheda e sensore: MAX 2 m
- Memoria d'intensità luminosa anche in assenza di rete
- Accensione graduale / Spegnimento graduale
- Accensione da presa comandata

Technical features

Dimmable independent electronic transformer halogen lamps and LED lamps

- Continuous sensorial or push button regulation
- No line plug polarity
- Maximum distance between circuit and control point 2 meters
- The light level is memorized unless the mains supply is cut off
- Soft start / Soft stop
- Switch-on from wall socket

S = Controllo a sfioramento - *Touch control*

PS = Controllo a sfioramento e pulsante
Touch and push button control



Trasformatore elettronico indipendente dimmerabile, per lampade alogene e LED dimmerabili

- Regolazione sensoriale o a pulsante continua
- Sensore indipendente dalla polarità di rete
- Distanza tra scheda e sensore: MAX 2 m
- Memoria d'intensità luminosa anche in assenza di rete
- Accensione graduale / Spegnimento graduale
- Accensione da presa comandata

Installazione

L'alimentatore elettronico deve essere impiegato esclusivamente su apparecchi di illuminazione in classe III. Rispettare i dati di targa, posizionare l'alimentatore lontano da fonti di calore. Limitare a 2 metri la lunghezza del cavo di collegamento al carico.

Dimmable independent electronic transformer halogen and LED lamps dimmable

- Continuous sensorial or push button regulation
- No line plug polarity
- Maximum distance between circuit and control point 2 meters
- The light level is memorized unless the mains supply is cut off
- Soft start / Soft stop
- Switch-on from wall socket

Installation

Use exclusively with lighting fixtures in Class III. Respect plate values indicated, keep transformer far from direct heat sources. Distance of connecting cable to load should not exceed 2 metres.

