

REATTORI CONVENZIONALI PER LAMPADIE FLUORESCENTI

CONVENTIONAL BALLAST FOR FLUORESCENT LAMPS



LED LICHTTECHNIK
LEUCHTENZUBEHÖR


A: Rütlistrasse 18, CH-8952 Schlieren

T: +41 (0)44 730 56 56 W: www.elektrogros.ch

E: info@elektrogros.ch E: shop@elektrogros.ch




Indice efficienza energetica **A3** vendibili in CEE solo come parti di ricambio o in paesi extra CEE
Energy efficiency index **A3** can be sold in the CEE market only as spare parts, or extra CEE countries



Reattori convenzionali per lampade fluorescenti a catodi preriscaldati

Built-in conventional ballast for fluorescent lamps with pre-heated cathodes

Article	W Lamp	A Lampada	Δt °C	μF rifasam.	Lamp holder		LPH mm		Code	Euro cad.
FC4	1xFD-4-E	0,160	65	2	G5	340	85X40X28	20	S53101	7,20
	1xFD-4-E	0,167								
	1xFD-4-E	0,160								
FC9	1xFSD-5-I	0,180	65	2	G23	340	85X40X28	20	S53103	7,20
	1xFSD-7-I	0,175			G23					
	1xFD-8-E	0,165			G5					
	1xFSD-9-I	0,160			G23					
	1xFSD-11-I	0,160			G23					
FC13	1xFSQ-10-I	0,190	65	2	G24d1	340	85X40X28	20	S53105	7,20
	1xFSQ-13-I	0,165			G24d1					
	1xFSM-13-I	0,165			GX24d1					
	1xFD-13-E	0,165			G5					
	2xFSD-5-I	0,190			G23					
	2xFD-6-E	0,160			G5					
	2xFSD-7-I	0,180			G23					
2xFSD-9-I	0,160	G23								
FC16	1xFSS-16-I	0,180	65	2	GR8	340	85X40X28	20	S53107	7,20
	1xFSS-16-E	0,180			GR10q					
	1xFD-16-E	0,190			G13					
	2xFD-8-E	0,170			G5					
FC18	1xFSQ-18-I	0,220	65	2	G24d2	340	85X40X28	20	S53109	7,20
	1xFSM-18-I	0,220			GX24d2					



Reattori convenzionali per lampade fluorescenti a catodi preriscaldati

Built-in conventional ballast for fluorescent lamps with pre-heated cathodes

Article	W Lamp	A Lampada	Δt °C	μF rifasam.		Lamp holder		LPH mm		Code	Euro cad.
				*	+						
F20	1xFD-18-E	0,370	70	2,7	4,5	G23	550	150X42X29	20	S53305	9,00
	1xFSD-18-E	0,375				2G11					
	1xFD-20-E	0,370				G13					
	1xFC-22-E	0,340				2G11					
	1xFSD-24-E	0,340				G24d3					
	1xFSQ-26-I	0,315									
F30	1xFD-30-E	0,365	70	4,5	3	G13	550	150X42X29	20	S53309	9,60
	2xFD-15-E	0,330				G13					
F32	1xFC-32-E	0,425	65	4,5	3,6	G10q	550	150X42X29	20	S53311	9,60
F40	1xFSD-36-E	0,430	70	3,4	4,5	2G11	550	150X42X29	20	S53313	9,60
	1xFD-36-E	0,430				G13					
	1xFD-40-E	0,430				G13					
	2xFD-18-E	0,370				G13					
	2xFD-20-E	0,370				G13					
F65	1xFD-58-E	0,670	70	5,3	7	G13	790	195X42X29	10	S53315	14,40
	1xFD-65-E	0,670				G13					

- * Parallelo/Parallel 250V
- + Serie/Series 400V



Starter Convenzionale
Conventional Starter

Article	W Lamp	t_a °C	$\varnothing D$ mm	L mm		Code	Euro cad.
SC422	4÷22	-25...+70	21	35	25	S53991	0,55
SC480	4÷80	-25...+70	21	35	25	S53993	0,55